

CM-300 Series Exit Switch

INSTALLATION INSTRUCTIONS


1. GENERAL DESCRIPTION

Camden CM-300 series illuminated Exit switches are available with stainless-steel single-gang faceplate (CM-300), or with Narrow jamb size faceplate (CM-310).

The 1/2" x 3/4" illuminated translucent button is easy to push, and supplied in momentary or

maintained models. Red buttons are standard but blue and green are also available.

The supplied LED will work on 12 volts, or 24 volts (using supplied inline resistor).



CM-300RE

CM-310E

2. SPECIFICATIONS

Models	CM-300	CM-310
Dimensions	2.75" W x 4.5" H x 1 5/16" (70mm x 114mm x 33mm)	1.75" W x 4.5" H x 1 5/16" (44mm x 114mm x 33mm)
Contacts	Mom. / Maint.	
Switch Rating	10 amps @ 125 VAC	
Electrical Life	100,000 @ rated capacity	
Mounting	2 x #6-32 machine screws	
Lens Colour	Red, Green, or Blue	
Legend	'EXIT'	
LED Voltage	12 or 24 V DC	

3. WARRANTY

Camden Door Controls guarantees the CM-300 series to be free from manufacturing defects for 3 years from date of sale. If during the first 3 years a CM-300 series switch fails to perform correctly, it may be returned to our factory where it will be repaired or replaced (at our discretion) without charge. There is no warranty for bulb damage due to over voltage! Except as stated herein, Camden extends no warranties expressed or implied regarding function, performance or service.

2. INSTALLATION

Mounting

1. The colour coded leads are permanently soldered onto the back of the switch. The Red & Black wires are for the light.
2. For normally open circuits use the Blue & Green wires.
For normally closed circuits use the Yellow & Green wires.
3. Tuck wiring into box and fasten switch plate using screws provided (CM-300), or tuck wiring into frame and fasten to frame using screws provided (CM-310).

